

MKIII (NEMA) BATTERY INSTALLATION

1. Turn unit off, by moving toggle switch located on the bottom of the unit to the off position.
2. Using a phillips head screwdriver, loosen the 4 screws location on the front panel (one in each corner).
3. Gently pull the cover with the solar panel forward, until you see the 2 conductor wire/plug coming from the solar panel. Unplug this cable from the motherboard.
4. Remove the battery from the compartment and disconnect the two leads from the battery.
5. Install new battery, by connecting the leads on the battery and placing it back into the compartment.
6. Re-install the cover/solar panel and connect the plug removed in step 3.
7. Tighten screws on front panel, and turn unit back on using the toggle switch.